

WHAT IS CLAIMED IS:

1. A signal processing system capable of compensating for the channel response characteristics of an input waveform, comprising:
- input specifications for specifying the design of a filter, including:
 - channel response characteristics defining the response characteristics of a channel used to acquire said input waveform; and
 - user specifications for specifying a desired frequency response and a degree of compliance to the desired frequency response;
 - a filter builder for generating coefficients for said filter and outputting final performance specifications, having:
 - a compensation filter generator for generating coefficients corresponding to a compensation response on the basis of the inverse of the channel response characteristics; and
 - a response filter generator for generating coefficients corresponding to a combination of an ideal response and a noise reduction response on the basis of the user specifications; and
 - said filter for filtering said input waveform and outputting an overall response waveform having said desired frequency response, comprising:
 - a filter coefficient cache for storing the coefficients generated by said filter builder;
 - a compensation filter portion for filtering said input waveform using the coefficients stored in said filter coefficient cache corresponding to said compensation response; and

Sub
at

a response filter portion having a response filter stage and a noise reduction stage for filtering the compensated waveform output from said compensation filter portion and outputting said overall response waveform; said response filter portion filtering using the coefficients stored in said filter coefficient cache corresponding to said combination of said ideal response and said noise reduction response.

2. The signal processing system according to claim 1, wherein said filter is implemented as an infinite impulse response (IIR) filter.
3. The signal processing system according to claim 1, wherein said filter is implemented as a finite impulse response (FIR) filter.
4. The signal processing system according to claim 1, wherein said channel response characteristics are predetermined based on a reference signal and the reference signal as acquired by said channel.
5. The signal processing system according to claim 1, wherein said user specifications comprise a bandwidth, a response optimization, a compensation compliance, and a filter implementation type.
6. The signal processing system according to claim 5, wherein said response optimization is a pulse response optimization implemented using a Besselworth filter.

2022015005001

Sub
ac

7. The signal processing system according to claim 5, wherein said response optimization is a noise performance optimization implemented using a Butterworth filter.

8. The signal processing system according to claim 5, wherein said response optimization is a flatness optimization implemented using a Butterworth filter.

9. The signal processing system according to claim 5, wherein said filter implementation type is finite impulse response (FIR) or infinite impulse response (IIR).

10. The signal processing system according to claim 1, wherein said user specifications default to predetermined values.

11. A signal processing element for filtering an input digital waveform, comprising:

a filter builder for generating filter coefficients on the basis of a channel frequency response and a user response characteristics, said channel frequency response being determined on the basis of a response input and a correction input;

an infinite impulse response (IIR) filter having an IIR input for said input digital waveform and an IIR coefficient input connected to said filter builder; said IIR filter producing an IIR filtered waveform from the input digital waveform on the basis of the filter coefficients generated by said filter builder;

10090051-022702

[illegible]

13. The signal processing element according to claim 11, wherein said filter builder generates filter coefficients for said FIR filter or said IIR filter on the basis of said output selector switch.

14. The signal processing element according to claim 11, wherein said filter builder has channel, compensation, shaper, and noise reduction outputs for evaluating the performance of the filtering.

15. The signal processing element according to claim 11, wherein said response input is a known input response and said correction input is a measured input response as acquired by an input channel.

Feb 1
1991

16. The signal processing element according to claim 11, wherein said user response characteristics are used to generate filter coefficients corresponding to an arbitrary response portion of the filter.

17. The signal processing element according to claim 11, wherein said user response characteristics comprise a bandwidth, a response optimization, a compensation compliance, and a filter implementation type.

18. The signal processing element according to claim 17, wherein said response optimization is a pulse response optimization implemented using a Besselworth filter.

19. The signal processing element according to claim 17, wherein said response optimization is a noise performance optimization implemented using a Butterworth filter.

20. The signal processing element according to claim 17, wherein said response optimization is a flatness optimization implemented using a Butterworth filter.

21. The signal processing element according to claim 17, wherein said filter implementation type is FIR or IIR.

10090051-022702

| 姓名 | 性别 | 出生年月 | 籍贯 | 民族 | 文化程度 | 职业 | 工作单位 | 住址 | 联系电话 | 电子邮箱 | 备注 |
|-----|----|---------|------|----|------|-----|---------|---------|-------------|---------------------|----|
| 王德胜 | 男 | 1975.03 | 山东烟台 | 汉族 | 高中 | 农民 | 烟台市莱山区 | 烟台市莱山区 | 13906312345 | 13906312345@qq.com | |
| 李国强 | 男 | 1980.07 | 河南郑州 | 汉族 | 大学 | 教师 | 郑州市金水区 | 郑州市金水区 | 15837123456 | 15837123456@163.com | |
| 张小明 | 男 | 1985.12 | 江苏苏州 | 汉族 | 初中 | 工人 | 苏州市工业园区 | 苏州市工业园区 | 18921234567 | 18921234567@163.com | |
| 赵小红 | 女 | 1990.05 | 四川成都 | 汉族 | 高中 | 学生 | 成都市武侯区 | 成都市武侯区 | 13528123456 | 13528123456@163.com | |
| 陈伟强 | 男 | 1978.09 | 广东广州 | 汉族 | 大学 | 工程师 | 广州市天河区 | 广州市天河区 | 13802123456 | 13802123456@163.com | |
| 刘丽娟 | 女 | 1982.11 | 湖北武汉 | 汉族 | 高中 | 护士 | 武汉市江汉区 | 武汉市江汉区 | 15927123456 | 15927123456@163.com | |
| 孙志强 | 男 | 1970.04 | 浙江杭州 | 汉族 | 大学 | 经理 | 杭州市西湖区 | 杭州市西湖区 | 13757123456 | 13757123456@163.com | |
| 周美玲 | 女 | 1988.06 | 湖南长沙 | 汉族 | 高中 | 文员 | 长沙市岳麓区 | 长沙市岳麓区 | 15273123456 | 15273123456@163.com | |
| 吴大伟 | 男 | 1972.08 | 安徽合肥 | 汉族 | 大学 | 程序员 | 合肥市蜀山区 | 合肥市蜀山区 | 13605123456 | 13605123456@163.com | |
| 郑小芳 | 女 | 1983.10 | 福建厦门 | 汉族 | 高中 | 销售 | 厦门市思明区 | 厦门市思明区 | 13959123456 | 13959123456@163.com | |
| 冯国强 | 男 | 1976.02 | 广西桂林 | 汉族 | 大学 | 教师 | 桂林市七星区 | 桂林市七星区 | 13877123456 | 13877123456@163.com | |
| 马小红 | 女 | 1987.01 | 江西九江 | 汉族 | 高中 | 学生 | 九江市濂溪区 | 九江市濂溪区 | 15879123456 | 15879123456@163.com | |
| 周志强 | 男 | 1979.03 | 山西太原 | 汉族 | 大学 | 工程师 | 太原市迎泽区 | 太原市迎泽区 | 13633123456 | 13633123456@163.com | |
| 李美娟 | 女 | 1984.05 | 云南昆明 | 汉族 | 高中 | 文员 | 昆明市五华区 | 昆明市五华区 | 15987123456 | 15987123456@163.com | |
| 吴大伟 | 男 | 1973.07 | 贵州贵阳 | 汉族 | 大学 | 经理 | 贵阳市南明区 | 贵阳市南明区 | 13785123456 | 13785123456@163.com | |
| 郑小芳 | 女 | 1986.09 | 四川成都 | 汉族 | 高中 | 学生 | 成都市武侯区 | 成都市武侯区 | 13528123456 | 13528123456@163.com | |
| 冯国强 | 男 | 1977.11 | 广东广州 | 汉族 | 大学 | 工程师 | 广州市天河区 | 广州市天河区 | 13802123456 | 13802123456@163.com | |
| 马小红 | 女 | 1981.12 | 湖北武汉 | 汉族 | 高中 | 护士 | 武汉市江汉区 | 武汉市江汉区 | 15927123456 | 15927123456@163.com | |
| 周志强 | 男 | 1974.04 | 浙江杭州 | 汉族 | 大学 | 经理 | 杭州市西湖区 | 杭州市西湖区 | 13757123456 | 13757123456@163.com | |
| 李美娟 | 女 | 1989.06 | 湖南长沙 | 汉族 | 高中 | 文员 | 长沙市岳麓区 | 长沙市岳麓区 | 15273123456 | 15273123456@163.com | |
| 吴大伟 | 男 | 1971.08 | 安徽合肥 | 汉族 | 大学 | 程序员 | 合肥市蜀山区 | 合肥市蜀山区 | 13605123456 | 13605123456@163.com | |
| 郑小芳 | 女 | 1985.10 | 福建厦门 | 汉族 | 高中 | 销售 | 厦门市思明区 | 厦门市思明区 | 13959123456 | 13959123456@163.com | |
| 冯国强 | 男 | 1976.12 | 广西桂林 | 汉族 | 大学 | 教师 | 桂林市七星区 | 桂林市七星区 | 13877123456 | 13877123456@163.com | |
| 马小红 | 女 | 1982.01 | 江西九江 | 汉族 | 高中 | 学生 | 九江市濂溪区 | 九江市濂溪区 | 15879123456 | 15879123456@163.com | |
| 周志强 | 男 | 1978.03 | 山西太原 | 汉族 | 大学 | 工程师 | 太原市迎泽区 | 太原市迎泽区 | 13633123456 | 13633123456@163.com | |
| 李美娟 | 女 | 1983.05 | 云南昆明 | 汉族 | 高中 | 文员 | 昆明市五华区 | 昆明市五华区 | 15987123456 | 15987123456@163.com | |
| 吴大伟 | 男 | 1972.07 | 贵州贵阳 | 汉族 | 大学 | 经理 | 贵阳市南明区 | 贵阳市南明区 | 13785123456 | 13785123456@163.com | |
| 郑小芳 | 女 | 1987.09 | 四川成都 | 汉族 | 高中 | 学生 | 成都市武侯区 | 成都市武侯区 | 13528123456 | 13528123456@163.com | |
| 冯国强 | 男 | 1977.11 | 广东广州 | 汉族 | 大学 | 工程师 | 广州市天河区 | 广州市天河区 | 13802123456 | 13802123456@163.com | |
| 马小红 | 女 | 1981.12 | 湖北武汉 | 汉族 | 高中 | 护士 | 武汉市江汉区 | 武汉市江汉区 | 15927123456 | 15927123456@163.com | |
| 周志强 | 男 | 1974.04 | 浙江杭州 | 汉族 | 大学 | 经理 | 杭州市西湖区 | 杭州市西湖区 | 13757123456 | 13757123456@163.com | |
| 李美娟 | 女 | 1989.06 | 湖南长沙 | 汉族 | 高中 | 文员 | | | | | |

generating a compensation portion of a filter on the basis of an input channel response, using the steps of:

designing an analog filter emulating the pre-warped input channel response by making an initial filter guess and iterating the coefficients of said initial filter guess to minimize a mean-squared error;

digitizing the inverted analog filter to produce said compensation portion of said filter using a bilinear transformation; and

24. The method according to claim 23, further comprising the step of
 25. applying an arbitrary response portion of said filter on the basis of an input user
 26. instructions, wherein said input digital waveform is filtered using said arbitrary
 27. response portion of said filter, thereby producing a filtered digital waveform having the
 28. desired response characteristics.

Sub
Pat

25. The method according to claim 24, wherein said input user specifications comprise a bandwidth, a response optimization, a compensation compliance, and a filter implementation type.

26. The method according to claim 24, wherein said arbitrary response portion of said filter comprises a shaper and a noise reducer.

27. The method according to claim 24, wherein said input user specifications default to predetermined values.

28. The method according to claim 23, wherein said filter is implemented as an infinite impulse response (IIR) filter.

29. The method according to claim 23, wherein said filter is implemented as a finite impulse response (FIR) filter.

30. The signal processing system according to claim 23, wherein said input channel response is predetermined based on a reference signal and the reference signal as acquired by said channel.

31. ~~The method according to claim 23, wherein said response optimization is a pulse response optimization implemented using a Besselworth filter.~~

32. ~~The method according to claim 23, wherein said response optimization is a noise performance optimization implemented using a Butterworth filter.~~

33. ~~The method according to claim 23, wherein said response optimization is a flatness optimization implemented using a Butterworth filter.~~

*Sub
a1*
34. ~~The method according to claim 23, wherein said filter implementation type is FIR or IIR.~~

35. ~~The method according to claim 23, wherein the coefficients of said initial filter guess are iterated until said mean-squared error is less than a compensation compliance specified in said input user specifications.~~

1000054-02202